

ISP CORE 16 - SPECIFICATIONS

		ISP Core 16
		131 331 3
Main Features	Auro-3D / Dolby Atmos / DTS:X Pro / IMAX Enhanced	\/\/\/\/
	StormXT channel expander SphereAudio - binaural immersive sound for headphones	Optional -
	Dirac Live room correction	√
	Dirac Live Bass Control module StormMonitoring - remote monitoring	√ √
	Statistically remote managing	·
Multichannel /	Output channels	16
Surround Processing	Decoding / upmixing channels Input sampling rate supported	16 up to 192 kHz
	Post processing sampling rate	48 kHz
	Dirac Live runtime with high resolution mixed-phase filters	√
	Bass management : Standard & Expert Flexible bass routing (up to 6 zones, Expert mode)	✓ Optional
	Multi-subwoofer channels	Unlimited
	Multi-way crossover (6 to 48 dB/oct, Linkwitz-Riley, Butterworth)	up to 4 per channel
	Parametric EQ per channel	up to 20 filters
HDMI	HDMI inputs / outputs	7/2
	Standard	HDMI 2.0b / HDCP 2.2
	Matrix capability for multi-room 4K UHD, rec BT709 and rec BT2020	Optional ✓
	High Dynamic Range: HDR10 / HLG / Dolby Vision	<i>\</i> \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \
	Color space and subsampling	RGB, YCbCr, 4:4:4, 4:2:2, 4:2:0
	Deep color (12 bpc) Max. resolution support (18 Gbps)	✓ 4K 60fps 4:4:4 8bpc
	3D / OSD	V/V
	ARC / eARC	√ / √
Audio Inputs	Streaming: Roon ready end point	✓
Providence	Digital input: coaxial / optical	3/3
	Digital input: AES/EBU 16ch (DCI compatible)	-
	Analog stereo inputs, balanced : XLR Analog stereo inputs, unbalanced: RCA	- 4
	· · · · · · · · · · · · · · · · · · ·	
Audio Outputs	Analog main outputs, balanced (ch 1 to 16)	XLR
	Analog main outputs, balanced (ch 17 to 24) Analog main outputs, balanced (ch 25 to 32)	- -
	Analog main outputs, balanced (ch 17 to 32)	-
	Stereo downmix Zone2 outputs Digital output: AES/EBU 32ch (ch 1 to 32)	Digital Optical
	Digital output: AVB 32ch (ch 1 to 32)	-
Audio Inputs/		
Outputs	Digital AES67 / Dante compatible (Audio over IP): 32ch out / 32ch in	
Set-up Management	Audio zone configuration	✓
	Individual theater and zone source selection (Main & Zone2)	✓
	Theater and zones listening presets Dirac Live profiles	Unlimited 10 per Theater / Zone
	Backup and restore of set-up	v per meater / zone
	Firmware update via USB / network	√ / √
Control Inputs /		
Outputs	USB type A (upgrade and monitoring)	2
Dutputs		
Dutputs	Ethernet / Wi-Fi	√ / - 4 (out)
Outputs	Ethernet / Wi-Fi Output trigger control IR remote ports, in / out (input loop through)	√/- 4 (out) 1/1
Dutputs	Output trigger control	4 (out)
	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel	4 (out) 1 / 1 ✓
Control / Custom	Output trigger control IR remote ports, in / out (input loop through)	4 (out) 1 / 1
Control / Custom	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator	4 (out) 1 / 1 √ √ (TFT 5") √
Control / Custom	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control	4 (out) 1 / 1 √ √ (TFT 5") √ √
Control / Custom	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control4, Savant, RTI, ELAN home automation drivers	4 (out) 1 / 1 √ √ (TFT 5") √
Control / Custom	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control4, Savant, RTI, ELAN home automation drivers Logitech Harmony IR database integration	4 (out) 1 / 1
Control / Custom	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control4, Savant, RTI, ELAN home automation drivers	4 (out) 1 / 1
Control / Custom nstallation	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control4, Savant, RTI, ELAN home automation drivers Logitech Harmony IR database integration	4 (out) 1 / 1
Control / Custom nstallation	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control 4, Savant, RTI, ELAN home automation drivers Logitech Harmony IR database integration IR remote control handset Voltage range Type	4 (out) 1 / 1
Control / Custom nstallation	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control4, Savant, RTI, ELAN home automation drivers Logitech Harmony IR database integration IR remote control handset	4 (out) 1 / 1
Control / Custom nstallation Power Supply	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control 4, Savant, RTI, ELAN home automation drivers Logitech Harmony IR database integration IR remote control handset Voltage range Type	4 (out) 1 / 1
Control / Custom Installation	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control 4, Savant, RTI, ELAN home automation drivers Logitech Harmony IR database integration IR remote control handset Voltage range Type Range selection Home / rack (removable ears) Net weight (kg / lbs)	4 (out) 1 / 1
Control / Custom Installation Power Supply Casing	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control4, Savant, RTI, ELAN home automation drivers Logitech Harmony IR database integration IR remote control handset Voltage range Type Range selection Home / rack (removable ears) Net weight (kg / lbs) Size	4 (out) 1/1 / / (IFT 5") / / / / / / / / / / / / /
Control / Custom Installation	Output trigger control IR remote ports, in / out (input loop through) IR remote control sensor in front panel Front panel display Advanced control via front panel Web-based product configurator TCP/IP API based control StormRemote control application (iOS / Android) Crestron, Control 4, Savant, RTI, ELAN home automation drivers Logitech Harmony IR database integration IR remote control handset Voltage range Type Range selection Home / rack (removable ears) Net weight (kg / lbs)	4 (out) 1 / 1